

INVOLIGHT

LED SPOT50

USER MANUAL V1.0 EN

INTRODUCTION

- * LED SPOT50 rated for IP67 to use in any venue including outdoor and underwater
- * 36 quality high power LEDs, each LED is 1W, RGB color mixing
- * AUTO run when no DMX controlling
- * 4 DMX channels
- * Stand-alone operation with master/slave
- * with auto-switching power unit inside, auto adapts 100V-240V 50/60Hz

OPERATION

AUTO Mode:

This mode allows a single unit to auto change in Auto Mode.

- 1) Press <MENU> until "Auto" appears on the display, and press <ENTER>.

Master/Slave Mode:

This mode will allow you to link up to 32 units together without a controller.

- 1) Use standard DMX cables to daisy chain your units together via the DMX connector on the rear of the units. For longer cable runs we suggest a terminator at the last fixture. For more information about terminators

- 2) Choose a unit to function as the Master. The unit must be the first unit in line. Press <MENU> until "Auto" appears on the display, and press <ENTER>. Set A001 for all linking up units as slave units.

DMX Mode

This mode allows the unit to be controlled by any universal DMX controller. If you are unfamiliar with DMX

- 1) Press <MENU> until "A***" is displayed and press <ENTER>.
- 2) Scroll through to select the desired address, and press <ENTER>.

DMX Channel Value

- | | |
|-----------|---|
| Channel 1 | 0 Close; 1-127 Strobe speed; 128-255 Brightness |
| Channel 2 | 0-255 (R) Brightness of red color |
| Channel 3 | 0-255 (G) Brightness of green color |
| Channel 4 | 0-255 (B) Brightness of blue color |